



DIN CABLE for the Key-8 Keyer/Paddle

EI-KEY8DIN-B

The cable has stripped and tinned leads for DC power supply and the keyed output to transmitter. Audio output from the Key-8's internal side-tone oscillator is not provided for in this version of the cable. You may notice that there is an orange wire that has been trimmed flush with the outer insulation of the cable. This wire is connected in common with the red wire, i.e. the +DC supply. It could be used to power some other piece of equipment if necessary.

Wire assignments:

- Bare Wire - cable shield, common to the DC ground connection.
- Red Wire - +9 to +15V DC
- Black Wire - Power supply ground
- Yellow and brown wires - Keyer Output (to transmitter's key jack). These wires are connected to a relay inside the Key-8, so there is no "polarity," and the Key-8 can be used with transmitters that have either positive or negative keying circuits.